

B921C Two-line Keypad w/Touch keys, Inputs



The B921C keypad is an SDI2 bus compatible device. The keypad features capacitive touch keys, instead of the mechanical buttons found on most keypads. With a smooth, sleek surface, the keypad is easy to clean, and fits with any modern decor. The keypad has user adjustable options such as volume and brightness. The keypad has three programmable emergency keys, and four inputs. The keypad also shows two-line system messages for all areas.

Keypad languages

Available languages: English, Dutch, French, German, Hungarian, Italian, Portuguese, Spanish, Swedish.

System overview

- For commercial use, install the keypad in building entrances and areas with unrestricted access. Mounting a keypad near exterior doors in hotel or business lobbies allows people to identify the type and location of the emergency.
- For residential use, install the keypad near the front and rear entrances to the home. Install additional keypads in a kitchen or in a bedroom.
- Use multiple keypads in a large building with many separate areas of security. Program multiple keypads to control multiple areas.
- Audible tones from the keypad sounder alert personnel to fire events and assist fire fighters in locating the keypad.

- ▶ 2-line LCD display with up to 32 character point, user, and area names
- ▶ Capacitive touch keys clean easily and are more resistant to wear than traditional mechanical buttons
- ▶ Situation sensitive on-screen help makes system operation simple and easy
- ▶ Highly visible on (arm)/alarm, ready to turn on (arm), power, trouble, and gas alarm indicators
- ▶ Four inputs provide simple, lower-cost point expansion

Functions

LCD display

The keypad uses words, numbers, and symbols to show the status of the security system. When several events occur, the keypad shows each event in order of priority.

Keys

Each keypad has 10 number keys, 7 function keys, and 6 navigation keys. When pressed, keys turn on keypad backlighting and emit the keypress tone (short beep). The function keys include programmable function keys and keys to initiate arming and bypassing with one keypress.

Audible tones

The keypad has a built-in speaker that produces several distinct warning tones. The tones are differentiated so that the user can recognize an event simply by hearing its associated tone. The keypad backlight illuminates when it emits an audible tone. Users can use a passcode to silence the tone.

Status indicators

The status indicators on the keypad provide a quick visual reference for system status.

✓	The indicator lights when the system is ready to turn on (arm).
🔒	The indicator lights when the system is on (armed).
⚠️	The indicator lights when there is a trouble condition.

GAS	The indicator lights when dangerous gases are present including carbon monoxide (NFPA 720).
*	The indicator lights when the system has power.

Regulatory information

Region	Regulatory compliance/quality marks	
USA	CSFM	
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 985 - Household Fire Warning System Units (6th edition)
	UL	UL 1023 - Household Burglar Alarm System Units, SIA-CP-01:2010
Canada	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	IC	ICES-003 - Information Technology Equipment (ITE)
	ULC	CAN/ULC S545 - Residential Fire Warning System Control Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
	ULC	Underwriters Laboratories of Canada S1871-20121210

Installation/configuration notes

Mounting considerations

Mount in indoor, dry locations.

Power supply

A compatible control panel supplies the power and data requirements to the keypad through a four-wire connection.

Enclosure and wiring

The sliding self-locking enclosure has an integrated bubble level and custom gap-free, lift-gate style terminal blocks to make installation easier.

Compatible control panels

B9512G
 B8512G
 B6612
 B6512
 B5612
 B4612
 B5512 firmware v2.02 and higher
 B4512 firmware v2.02 and higher

B3512 firmware v2.02 and higher
 D9412GV4/D7412GV4 firmware v2.02 and higher

Parts included

Quantity	Component
1	Keypad
1	Hardware pack
4	1k Ω EOL Resistors
1	Installation Guide
1	User's Quick Reference Guide

Technical specifications

Properties

Dimensions	6.2 in x 4.7 in x 1 in (158 mm x 120 mm x 26 mm)
Weight	11.3 oz (0.32 kg)
Material	Acrylonitrile butadiene styrene (ABS) Poly(methyl methacrylate) (PMMA)
Display window	2 line display 18 characters per line
Indicators	Illuminated keys Status indicators Warning and indicating tones
Inputs	4 (four) 1k Ω supervised inputs

Environmental considerations

Relative humidity	5% to 93% at +32°C (+90°F) non-condensing
Temperature (operating)	0°C to +50°C (+32°F to +122°F)
Mounting considerations	Mount in dry indoor locations.

Power requirements

Current	Standby: 45 mA Alarm: 85 mA
Voltage (input)	12 VDC nominal

Wiring

Terminal wire size	12 AWG to 22 AWG (2.0 mm to 0.65 mm)
--------------------	--------------------------------------

SDI2 wiring	Maximum distance - wire size (unshielded wire only): 700 ft (213 m) - 22 AWG (0.65 mm) 1000 ft (305 m) - 18 AWG (1.02 mm)
-------------	---

Ordering information

B921C Two-line Keypad w/Touch keys, Inputs

Two-line alphanumeric keypad with inputs and capacitive touch keys in black.

Available languages: English, Dutch, French, German, Hungarian, Italian, Portuguese, Spanish, Swedish.

Order number **B921C | F.01U.323.786 F.01U.385.734**

Accessories

B56 Keypad surface mount box

Surface mount box for mounting a keypad to concrete or block.

Order number **B56 | F.01U.295.834**

B96 Trim plate for keypad

Cover the wall footprint of previous keypads when replacing them with the new, slim design of B Series keypads. The white trim bezel is 8.6 in x 6.3 in x 0.12 in (22 mm x 16 mm x 3 mm).

Order number **B96 | F.01U.272.856**

Services

EWE-KEYPAD-IW 12 mths wrty ext Keypad

12 months warranty extension

Order number **EWE-KEYPAD-IW**



<https://www.boschsecurity.com>