

B942W-PL Touch screen KP, Private Label



- ▶ Indented label location for your personalized logo
- ▶ Slim, modern design blends with any décor combined with color graphic touch screen display uses a combination of simple icons and text for easy operation
- ▶ Built-in presence detector lights the display when user approaches keypad
- ▶ Built-in proximity reader allows use of a token or card as replacement for a passcode, or for use with dual authentication for high security areas
- ▶ Four inputs and one output provide cost effective expansion

The keypad is an SDI2 bus compatible device. The keypad features an illuminated touch screen and graphical interface. With an elegant design and low profile, the keypad fits with any modern decor. Each keypad has user adjustable options such as volume and brightness. They have four inputs and one output. The keypad shows system messages for all areas.

Keypad languages

The following languages are available:

- English
- Chinese
- Dutch
- French
- German
- Greek
- Italian
- Hungarian
- Polish
- Portuguese
- Spanish
- Swedish

System overview

- For commercial use, install the keypad in building entrances and areas with unrestricted access. Mounting a keypad near exterior doors in hotel or business lobbies allows people to identify the type and location of the emergency.
- For residential use, install the keypad near the front and rear entrances to the home. Install additional keypads in a kitchen or in a bedroom.
- Use multiple keypads in a large building with many separate areas of security. Program multiple keypads to control multiple areas.
- Audible tones from the keypad sounder alert personnel to fire events and assist fire fighters in locating the keypad.

Functions

Display

The touch screen display uses icons, words, numbers, and symbols to show the status of the security system and for interacting with the security system. When several events occur, the keypad shows each event in order of priority. The keypad detects when a user approaches and automatically activates the display.

User icons and keys






The keypad greets the user with a home screen that shows the system status at one glance using a large icon. The user can change the system status by simply touching this home screen icon. The touch screen display also offers icons on the ribbon bar. These visually pleasing graphical icons are easy to use for accessing menus and other options. The keypad has a variety of keyboards for entering alphanumeric characters. The keypad screen has numeric keys and one function [CMD] key. When pressed, keys emit a muted beep. Use the keyboards for entering passcodes, activating commands, and entering alphanumeric characters.

Audible tones

The keypad has a built-in speaker that produces several distinct warning tones. The tones are differentiated so that the user can recognize an event simply by hearing its associated tone. The keypad backlight illuminates when it emits an audible tone. Users can use a passcode or credential to silence the tone.

Status indicators

The status indicators on the keypad provide a quick visual reference for system status.

	The indicator lights when the system is ready to turn on (arm).
	The indicator lights when the system is on (armed).
	The indicator lights when there is a trouble condition.
	The indicator lights when dangerous gases are present including carbon monoxide (NFPA 720).
	The indicator lights when the system has power.

Proximity reader

The proximity reader allows users to use a token or card in place of a passcode to turn on or off the security system. The proximity reader supports EM4102 (125 kHz) credentials. The Bosch ACA-ATR13-RFID tag and Bosch ACD-ATR11ISO-RFID card are examples.

Installation/configuration notes

Power supply

A compatible control panel supplies the power and data requirements to the keypad through a four-wire connection.

Mounting and wiring

Mount in dry indoor locations. Includes a slim mounting plate for recessing wiring, and a surface mounting plate for surface mounting and wiring.

Compatible control panels

B9512G
B8512G

B6512

B5512 firmware v2.03 and higher

B4512 firmware v2.03 and higher

B3512 firmware v2.03 and higher

D9412GV4/D7412GV4 v2.03 and higher

Parts included

Quantity	Component
1	Keypad
2	Mounting plates (slim and surface)
1	Hardware pack
4	1k Ω EOL Resistors
1	Installation Guide
1	User's Quick Reference Guide

Technical specifications

Mechanical

Dimensions (H x W x D) (mm)	120 mm x 158 mm x 16.5 mm
Dimensions (H x W x D) (in)	4.7 in x 6.2 in x 0.65 in
Weight (kg)	0.32 kg
Weight (oz)	11.3 oz
Material	Acrylonitrile butadiene styrene (ABS) Poly(methyl methacrylate) (PMMA)
Display window	Touch screen Multi-line messages
Indicators	Power indicator LED Status indicators Main icon Warning and indicating tones
Terminal wire size	1.02 mm-0.65 mm (18 AWG-22 AWG)
SDI2 wiring with prox detector disabled	Maximum distance - wire size (unshielded wire only) 61 m (200 ft) - 0.65 mm (22 AWG) 159 m (520 ft) - 1.02 mm (18 AWG)
SDI2 wiring with prox detector enabled	Maximum distance - wire size (unshielded wire only) 46 m (150 ft) - 0.65 mm (22 AWG)

	119 m (390 ft) - 1.02 mm (18 AWG)
--	-----------------------------------

Environmental

Operating relative humidity, non-condensing (%)	5% – 93%
Operating temperature (°C)	0 °C – 50 °C
Operating temperature (°F)	32 °F – 122 °F

Electrical

Current with proximity reader disabled	Standby: 200 mA Alarm: 300 mA
Current with proximity reader enabled	Standby: 300 mA Alarm: 400 mA
Output voltage (VDC)	12 VDC
Inputs	4 (four) 1k Ω supervised inputs
Output	1 (one) NO (normally open) contact
On-board points voltage ranges	Open: 2.2-5.0 VDC Normal: 1.4-1.8 VDC Short: 0.0-1.0 VDC Short circuit current: 2.3 mA
Relay contact rating	24 VDC, 1 A, power factor: 1

Ordering information

B942W-PL Touch screen KP, Private Label

SDI2 touch screen keypad with inputs and one output.
Available languages: English, Chinese, Dutch, French, German, Greek, Italian, Hungarian, Polish, Portuguese, Spanish, Swedish.

Order number **B942W-PL | F.01U.425.329**

Accessories

B56 Keypad surface mount box

Surface mount box for mounting a keypad to concrete or block.

Order number **B56 | F.01U.295.834**

B96 Trim plate for keypad

Cover the wall footprint of previous keypads when replacing them with the new, slim design of B Series keypads. The white trim bezel is 8.6 in x 6.3 in x 0.12 in (22 mm x 16 mm x 3 mm).

Order number **B96 | F.01U.272.856**



<https://www.boschsecurity.com>