

Solution 2000 / 3000 Control Panel



The Solution 2000 and Solution 3000 are new generation alarm control panels for small residential & commercial markets.

System overview

Supporting up to 8 fully programmable zones on the Solution 2000 and 16 fully programmable zones on the Solution 3000, this range of intrusion panels is suitable for any home, and even some commercial premises.

With support for up to four keypads on both panels and the ability to be split into two separate partitions on the Solution 3000, you have the flexibility of one security system that can act as two.

Functions

User Interfaces

The Solution 2000 and 3000 control panels have the variety of keypad options, including LCD Icon, LCD Alphanumeric, and various touchscreen options that are simple to use.

Wireless

The Solution 2000 supports the WE800EV2 wireless receiver for wireless keyfob control, while the Solution 3000 supports both the WE800EV2 and the option to integrate with the Bosch RADION range of wireless transmitters.

Communication

Solution 2000 and 3000 also have available a range of communications extension modules that integrate directly with the panel and provide options such as mobile communications via GPRS networks, along with IP reporting through the internet.

- ▶ 8/16 Fully Programmable Zones
- ▶ 33 Codes - 1 Installers, 32 User Codes
- ▶ 16 Wireless Devices (on Solution 3000)
- ▶ Partitionable into 2 Separate Areas
- ▶ STAY / AWAY Arming Options

The IP module includes CSV-IP communications technology and makes the panels fully NBN-ready / Fiber compatible with the majority of monitoring centers in Australia, New Zealand and Asia Pacific who can handle the IP communications from the Solution 2000 and 3000.

Remote Security Control Plus (RSC+) app

Remote Security Control Plus (RSC+) app allows users to control their security systems remotely from mobile devices such as phones and tablets. You can arm / disarm the control panel and control connected devices such as lighting and A/C, and select the events you want to receive push notifications.

Regulatory information

Australia	RCM AS/CA S002:2010
New Zealand	Telepermit
Europe	PCE - EN61000-3:2007/A1:2011 EN50130-4:2011

Technical specifications

Power Requirements

Primary	TF008 Plug Pack (only sold in Australia)
Secondary	12 VDC, 6.5Ah from rechargeable sealed lead/acid battery

Communications

Communications	CID, SIA, Email*, Domestic Dialing, CSV-IP, Push Notification*
	*Requires B426-M IP Communications Module or B450-M Universal Communications Module

Environmental Considerations

Temperature	0° to +45°C
Relative Humidity	10% to 95% non-condensing

Enclosure

Dimensions (H x W x D) (packed in carton)	306 x 262 x 84mm
Weight	2.5kg
Warranty	3 years

Ordering information

ICP-SOL2-P Control panel PCBA, 8-zone

Sold in Australia, New Zealand and APR region
Order number **ICP-SOL2-P | F.01U.292.968**

ICP-SOL3-P Control panel, 16-zone

Sold in Australia, New Zealand and APR region
Order number **ICP-SOL3-P | F.01U.292.967**

ICP-SOL2-APR Control panel, 8-zone, 230VAC

Only sold in APR region
Order number **ICP-SOL2-APR | F.01U.310.793**

ICP-SOL3-APR Control panel, 16-zone, 230VAC

Only sold in APR region
Order number **ICP-SOL3-APR | F.01U.310.794**

ICP-SOL2-PE Control panel with enclosure, 8 zone

Sold in Australia, New Zealand and APR region
Order number **ICP-SOL2-PE | F.01U.395.464**

ICP-SOL3-PE Control panel with enclosure, 16 zone

Sold in Australia, New Zealand and APR region
Order number **ICP-SOL3-PE | F.01U.395.467**

ICP-SOL-ENC Steel enclosure, solution, white

Use with ICP-SOL2-P and ICP-SOL3-P
Order number **ICP-SOL-ENC | F.01U.395.468**

Accessories

IUI-SOL-TS5 TouchOne Mini 5"

Only sold in Australia
Order number **IUI-SOL-TS5 | F.01U.335.887**

IUI-SOL-TS7 TOUCHONE 7" CODE PAD SDI2

Only sold in Australia
Order number **IUI-SOL-TS7 | F.01U.303.249**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
www.boschsecurity.com/xc/en/contact/
www.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Tel.: +49 (0)89 6290 0
Fax: +49 (0)89 6290 1020
de.securitysystems@bosch.com
www.boschsecurity.com

North America:
Bosch Security Systems, LLC
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
www.boschsecurity.com/xc/en/contact/
www.boschsecurity.com

IUI-SOL-TEXT LCD alphanumeric keypad

LCD text keypad, two lines with each 18 characters
Order number **IUI-SOL-TEXT | F.01U.301.795**

IUI-SOL-ICON LCD icon keypad, 16-zone

Shows 8 zones, provides LCD, and provides a protective door
Order number **IUI-SOL-ICON | F.01U.301.794**

B308 SDI2 8-Output Expansion Module

Provides 8 programmable relays.
Order number **B308 | F.01U.397.025 F.01U.385.672 F.01U.323.802**

B426-M Ethernet communication module, mobile

Supports Ethernet communication for remote programming and mobile apps on AMAX and Solution Series control panels
Order number **B426-M | F.01U.332.307 F.01U.386.953**

B450-M Plug-in communicator interface, mobile

Supports cellular communication for remote programming and mobile apps on AMAX and Solution Series control panels
Order number **B450-M | F.01U.332.308 F.01U.387.027**

Services

EWE-CTRCOM-IW 12 mths wrty ext Control Communicator

12 months warranty extension
Order number **EWE-CTRCOM-IW | F.01U.352.289**