
# **BATB Family Battery boxes\enclosures**

www.boschsecurity.com





- ► UL Approved as battery boxes and as enclosures for B9512G/B8512G/D9412GV4/D8412GV4/D7212GV4 control panels
- Suitable for residential/commercial fire or burglary applications
- ▶ Holds up to four auxiliary batteries

The BATB Family of battery box\enclosures is red for use in fire alarm systems. The BATB-40 provides a single level (two battery capacity) of battery storage. The optional BATB-SHELF battery shelf increases the battery capacity to four batteries. The BATB-80 comes with the BATB-SHELF mounted and holds up to four batteries.



### Informação

The actual number of batteries the battery box can hold depends on the size of the batteries. For battery box dimensions, see Technical Specifications. Mounting requirements depend on the total weight of the battery box/enclosure. For mounting information, see the *BATB-40/BATB-80 Installation manual*.

They are UL listed for use as enclosures for B9512G/B8512G/D9412GV4/D7412GV4/D7212GV4 control panels.



# Informação

When used as a control panel enclosure, the battery shelf must be removed.

## Certificações e aprovações

Região	Conformidade regulamentar/marcas de qualidade	
EUA	UL	ANSI/UL 864, Control Units and Accessories for Fire Alarm Systems
	CSFM	California State Fire Marshal

# Notas de instalação/configuração

## **Compatibility Information**

The BATB Battery boxes/enclosures are compatible with the following products:

Category	Product Description
Batteries	D126 12 V, 7 Ah Battery D1213 12 V, 1.3 Ah Battery D1218 12 V, 18 Ah Battery D1222 12 V, 2.2 Ah Battery D1224 12 V, 24 Ah Battery D1238 12 V, 38 Ah Battery D1240 12 V, 4 Ah Battery D1250 12 V, 5 Ah Battery
Control Panels	D9412GV4 246-point Control Communicator D7412GV4 75-point Control Communicator D7212GV4 40-point Control Communicator

# **Wiring Considerations**

For information on calculating the number and type of auxiliary batteries needed for your application and for wiring the auxiliary batteries, see the control panel's installation guide.



### Informação

When using multiple batteries in a battery box, each battery must be the same voltage, rating, and type.

# Dados técnicos

### **Battery Box Capacities**

### Batteries Storage - Total Dimensions (H x W x D)

BATB-40 without shelf	22 in. x 20.75 in. x 7.25 in. (55.9 cm x 52.7 cm x 18.4 cm)
BATB-80 bottom	22 in. x 20.75 in. x 7.25 in. (55.9 cm x 52.7 cm x 18.4 cm)
On shelf	~8 in. x 20.75 in. x 7.25 in. (~20.3 cm x 52.7 cm x 7.25 cm)

### **Number of Batteries**

BATB-40	Two
BATB-40 with shelf and BATB-80	Four

# Weight

Combined total with batteries	140 lb. (63.5 kg)
On Shelf (maximum)	50 lb. (22.6 kg)

#### Mechanical

Color	Red
Dimensions (H x W x D)	22 in. x 21 in. x 7.5 in. (55.9 cm x 53.3 cm x 19 cm)
Material	18 gauge (1.2 mm) cold-rolled steel

### Weight

<ul> <li>BATB-40 (without shelf):</li> </ul>	28.5 lb (13 kg)
• BATB-40 (with shelf) and BATB-80:	33 lb (15 kg)

### Informações para encomenda

# BATB-40 Battery box/enclosure, 22x21x7.25"

22 x 20.75 x 7.25" (56 x 53 x 18.5 cm). Holds two dry or wet cell batteries. Optional BATB-SHELF battery shelf increases number of batteries. Suitable for residential/commercial fire or burglary applications. Número de encomenda BATB-40

### Prateleira Opcional para Bateria BATB-SHELF

An optional battery shelf for the BATB-40. It allows up to two additional batteries to be placed in the battery box.

Número de encomenda BATB-SHELF

### BATB-80 Battery box/enclosure, 22x21x7.25"

14 x 20.75 x 7.25" (36 x 53 x 18.5 cm). Battery box/enclosure with shelf holds up to four dry or wet cell batteries. Suitable for residential/commercial fire or burglary applications.

Número de encomenda BATB-80

### Acessórios

### Chave de Substituição D102

Chave de substituição (#1358) para a fechadura D101. Número de encomenda **D102** 

### Representada por:

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5600 JB Eindhoven, The Netherlands Phone: + 31 40 2577 284 emea.securitysystems@bosch.com emea.boschsecurity.com Germany: Bosch Sicherheitssysteme GmbH Robert-Bosch-Ring 5 85630 Grasbrunn Germany www.boschsecurity.com