

PLM-WCP PLENA matrix Wall Control Panel

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Capacitive touch
- ▶ Source selection
- ▶ Volume control
- ▶ Powered from PLM-8M8
- ▶ Loop-through to connect with either more Wall Control Panels or Call Stations

The PLM-WCP PLENA matrix Wall Control Panel is an accessory of the PLM-8M8 PLENA matrix 8 channel DSP Matrix Mixer, and like any good accessory it has a complementary aesthetic design, but behind the good looks and sleek design, there is a product of substance and usability.

Installation couldn't be easier; Powered over standard CAT 5 from the PLM-8M8, the unit's communication is via RS485, this means that multiple PLM-WCPs can be daisy-chained together with the PLM-8CS 8 Zone Call Station, reducing cable runs and installation time.

Chức năng

Controls and indicators

Controls on the unit are all capacitive touch, and the LED lights are white, this gives a clean look and feel to the unit.

The select button simply toggles through each of the 4 possible selections. There are 2 configurations and during installation the DIP switch on the rear of the unit can be set to make the selection area either; A) 4

microphone/line inputs, so that each can be mixed individually in a zone, or B) 3 separate music sources that are switched, and an off.

Labeling

Labeling the unit couldn't be easier. Simply use the PC GUI software to print of the labels. This will also include white text on black background, so the aesthetics of the unit are kept.

Chứng nhận và Phê chuẩn

Safety	According to EN 60065
EMC emission	According to EN 55103-1
EMC immunity	According to EN 55103-2

Khu vực	Chứng nhận
Châu Âu	CE

Ghi chú Lắp đặt/Cấu hình

Loop Through.

Both PLM-WCP and PLM-8CS 8 Zone Call Station can be connected in series (daisy-chain), reducing the number of cable runs that need to be made in an installation. Both these units are powered from the PLM-8M8 8-channel DSP Matrix Mixer via the same CAT 5 cable.

Installation bracket

The unit is designed for surface mounting and comes complete with a bracket that fixes to the wall and the unit clips into the bracket. There are 3 cable entry options on the unit to make installation as easy as possible.

Bộ phận Đi kèm

Quantity	Components
1	PLM-WCP Wall Control Panel
1	Installation bracket
1	Safety documentation

Thông Số Kỹ Thuật

Electrical

Nguồn điện (cấp bởi PLM-8M8)	
Dải điện áp	30 - 50 VDC
Công suất tiêu thụ	0,5 W
Đầu nối	
RS485 nối tiếp	2x RJ45

Mechanical

Kích thước cơ sở (C x R x S)	130 x 100 x 30 mm 5,1 x 3,9 x 1,2 in
Lắp ráp	Giá gắn lắp vào bề mặt
Màu	Đen (RAL 9017) Bạc (RAL 9006)
Trọng lượng	Xấp xỉ 0,13 kg Xấp xỉ 0,29 lb

Environmental

Nhiệt độ hoạt động	từ -10 °C đến +45 °C
Nhiệt độ bảo quản	từ -40 °C đến +70 °C
Độ ẩm tương đối	<95%

Thông tin Đặt hàng

PLM-WCP PLENA matrix Wall Control Panel

Bảng điều khiển gắn tường, 8 vùng.

Số đặt hàng **PLM-WCP**

Đại diện bởi:

Vietnam
Bosch Security Systems
10th floor, 194 Golden Building,
473 Dien Bien Phu street,
ward 25, Binh Thanh District
84 Ho Chi Minh
Tel: +84 8 6258 3690
Fax: +84 8 6258 3693
www.boschsecurity.asia